



If A type protect should need increase installation

Note: Please make sure to use the correct size of the reflector.

1. Match the slot and place the Luminaire onto the reflector (Figure 1).
2. Turn the Luminaire clockwise until it is tightened (Figure 2).



INSTALLATION INSTRUCTIONS

Step1: Open a hole in the ceiling.


- 4 fits 4.7"min. to 5.2" max. ;
- 6 fits 6"min. to 7.3" max. ;
- 8 fits 7.4"min. to 8.9" max. ;

Step2: To move out the cover of the luminaire, press the both sides which contain knockout holes (Where to insert the cable) and pull out the cover upward at the same time.

Step3: Connect the wires. Input L connects to the black wire of the luminaire, N connects to the white wire, the ground connects to the green wire. (Connect Dimmer. Compatible with 0-10V dimmer. The driver PUR(D+) to the dimmer+(PUR), and the driver GRY(D-) to the dimmer-(GRY). Apply to CRLCX-10W-aaK-D, CRLCX-15W-aaK-D, CRLCX-20W-aaK-D)

Step4: Turn the arrow above the cover to the knockout direction, close it until it's tightned

Step5: Tighten up the spring to install the downlight to the ceiling and adjust the position.



NOTE

Please read this entire manual to fully understand and safely use this product. Specifications are subject to change without notice. Please visit our website the most recent user guide versions.

UNPACKING

- 1 Unpack and carefully examine the product.
- 2 Report any damage and save all packing materials if any part(s) were damaged during shipping.
- 3 Do not attempt to use this apparatus if it is damaged.

IMPORTANT SAFETY INFORMATION



CAUTION: Risk of Electric Shock

Suitable for Damp location. Access above ceiling required. Suitable for suspended ceilings.

READ ALL INSTRUCTIONS BEFORE INSTALLATION

- 1 Consult a qualified electrician to ensure correct branch circuit conductor.
- 2 The product should be installed and operated by a qualified electrician or technician in accordance with relevant local codes.
- 3 Risk of electric shock. Ensure that main power source is off when wiring or soldering the sections of the product.
- 4 Before installing this fixture or doing any maintenance, make sure to turn off the power supply at the circuit breaker or fuse box.
- 5 Check to make sure that all fixture connections have been properly made and the fixture is grounded to avoid potential electrical shocks.
- 6 Designed for use in AC120-347V,50/60Hz,0-10V dimming,protected circuit.

A type product contents :

- 1 Engine(without reflector)
- 2 Reflector
- 3 User manual

B type product contents :

- 1 LED Luminaire
- 2 User manual



Engine



4 inch



6 inch
Reflector



8 inch



LED
luminaire